

Pure Sine Wave Inverter 12V DC 2000W RCD



12V compatibility producing 230V AC Pure Sine Wave with 2000W of power

Will work with all 12V vehicles to produce 230V main power with 2000W of power for remote working



1. 4000W peak power rating. 2. RCD Protected

1. To handle large power loads when initially starting an electrical device. Will drop back down to 2000W continuous supply. 2. The integral Residual Current Device (RCD) replaces the need for an external RCD and will switch off the inverter in the event a fault is detected between live and earth. This protects the user against electric shocks.



2.1A USB Charging port

To charge mobile phones or smaller electronic devices at the same time as using the main power supply from the inverter.



Low battery alarm at 10V and low battery shutdown at 9.5V

Low battery alarm to alert operators to the fact that their vehicle battery is being drained and should stop using the inverter. When a vehicle's battery drops below 9.5V the inverter will switch off to preserve the vehicle battery to allow the vehicle to restart.

High-quality inverters for off-grid power needs

OSRAM POWERinvert PRO is an extensive range of professional heavy duty inverters for remote working. Available in either Pure Sine Wave or Modified Sine Wave for both 12V and 24V applications. OSRAM POWERinvert Pro inverters take the 12V or 24V DC vehicle electrical supply and invert into 230V AC mains power to run and operate electrical equipment from service vehicles. Pure Sine Wave Inverters produce a sine wave with the same frequency as mains power, with no distortion, to power sensitive electronics. Modified Inverters have distorted frequency, meaning they will power less complicated products such as fridges and power tools.



Product family datasheet

Technical data

Product description	Product information	Electrical Data		
	Number Of Phases	Input voltage range	Peak Amps	Continuous Power Rating (up to 12 hours)
Pure Sine Wave Inverter 12V DC 2000W	Single	(12V NOM) 9.5 V - 16.5 V	392	2000 W

Product description	Output voltage	No Load Current	Peak Power Rating (up to 200ms)	Input Current
Pure Sine Wave Inverter 12V DC 2000W	200 - 240 Vrms	< 2 A	2 * rated power for 0.2s	196 A


Product description	Physical Attributes & Dimensions	Dimensions & weight	Lifetime Data	Programmable features
	Height	Input Cable Gauge / Length	Guarantee	Thermal Protection
Pure Sine Wave Inverter 12V DC 2000W	120.0 mm	600mm, 2AWG	2 years	Yes

Product description	Certificates & standards	Environmental & Regulatory Information Information according Art. 33 of EU Regulation (EC) 1907/2006 (REACH)		
	Standards	Date of declaration	Primary article identifier	Candidate list substance 1
Pure Sine Wave Inverter 12V DC 2000W	CE / E- Mark	22-10-2024	4052899631069	Lead

Product description	CAS No. of substance 1	Safe use instruction	Declaration no. in SCIP database
Pure Sine Wave Inverter 12V DC 2000W	7439-92-1	Identifieringen av ämnet på kandidatlistan är tillräcklig för att artikeln ska kunna användas på ett säkert sätt.	5dcc0982-18e5-4e82-85f9-64e11b37f999

Product family datasheet

Download Data

File	
	User instruction POWERinvert PRO Pure Sine Wave Inverter

Safety advice

Tested and certified to the relevant EMC and LVD Directives.

Legal advice

CE Approved

Application advice

For more detailed application information and graphics please see product datasheet.

Disclaimer

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.